

陶瓷滤波器(10×8×4)技术指标:

- Center frequency : 4.5MHz,5.5MHz,6.0MHz,6.5MHz;
- Low insertion loss
- Low cost
- Applications: TV, VCR Stage, etc.



Part Number	Center Frequency	3dB Band Width KHz	20dB Band Width KHz	Insertion Loss(dB)	Spurious Attenuation(9-12MHz)	Input/Output impedance
LTS4.5MCB	4.5MHz	$\geq f_0 \pm 60$	≤ 600	≤ 6.0	$\geq 30\text{dB}$	1000 Ω
LTS4.5MDB	4.5MHz	$\geq f_0 \pm 70$	≤ 750	≤ 6.0	$\geq 30\text{dB}$	1000 Ω
LTS5.5MCB	5.5MHz	$\geq f_0 \pm 60$	≤ 600	≤ 6.0	$\geq 30\text{dB}$	600 Ω
LTS5.5MDB	5.5MHz	$\geq f_0 \pm 80$	≤ 750	≤ 6.0	$\geq 30\text{dB}$	600 Ω
LTS6.0MCB	6.0MHz	$\geq f_0 \pm 60$	≤ 600	≤ 6.0	$\geq 30\text{dB}$	470 Ω
LTS6.0MDB	6.0MHz	$\geq f_0 \pm 80$	≤ 750	≤ 6.0	$\geq 30\text{dB}$	470 Ω
LTS5.5MCB	6.5MHz	$\geq f_0 \pm 70$	≤ 650	≤ 6.0	$\geq 30\text{dB}$	470 Ω
LTS5.5MDB	6.5MHz	$\geq f_0 \pm 80$	≤ 800	≤ 6.0	$\geq 30\text{dB}$	470 Ω

PACKAGE:

UNITS:MM

